

Automatically regulates voltage variations.
Manual reset circuit breaker switch.
Input overload protection circuit breaker RJ-45/RJ-11.
Protection for ADSL Modems, Fax, Telephone.



FEATURES

- 4 NEMA 5-15R outlets.
- Surge and AVR protection.
- Holes for wall mount.
- LED indicators.
- The LED lights up when the AVR is on and regulating voltage.
- Automatic surge protection in all outlets.
- Standard protection for Internet ADSL Modem/Fax/Network.
- Protects your phone and data lines from dangerous and costly lightning surges.



STANDARD APPLICATIONS

- Personal computers
- Small Electronic Devices
- LCD/Plasma Displays
- Office Equipment

CONNECTIONS	FVR-1001
Input	
Output	

FEATURES		FVR-1001
CAPACITY		1000VA/500W
AC INPUT	Normal voltage	110V AC
	Input voltage range	96V AC to 140V AC
	Phase	1 Phase - 2 Wires
	Frequency	50/60Hz - Auto Sensing
AC OUTPUT	Output voltage range	107VAC - 132VAC
	Frequency	50 / 60Hz
OUTLETS	Surge Plus ASP Protection	4 NEMA 5-15R
PROTECTION	Network surge suppression	RJ-45/11
	Overload	Manual reset circuit switch
	Short Circuit	Manual reset circuit switch
LED	Regulating	Green LED on
ENVIRONMENT	Operating temperature	0 to 40°C
	Relative humidity	0 to 95% (non-condensing)
	Audible noise	< 40dB at 1 meter
PHYSICAL	Dimensions (D x W x H)	240 x 75 x 75mm
	Net weight	2.65lb/1.2kg
WARRANTY		2-year warranty with an optional 1-year extension, available through our Forza Carepack program