



www.xtechamericas.com



# XTS400

2.1 channel  
speaker system



Volume and bass  
controls



Easy  
setup



3.5mm  
connection



RMS  
12 watts



PC & Mac  
compatible

<b>Maximum power output (RMS):</b>	12 watts
<b>AC input:</b>	117-127V (50/60Hz autosensing)
<b>Controls:</b>	Power switch, volume and bass knobs

#### Speaker:

<b>Driver unit:</b>	3 inches
<b>Maximum power output (RMS):</b>	6 watts (3W per channel)
<b>Frequency:</b>	200Hz-18kHz
<b>Impedance:</b>	4Ω
<b>Sensitivity:</b>	400mV
<b>Signal to noise ratio:</b>	70dB

#### Subwoofer:

<b>Driver unit:</b>	4 inches
<b>Maximum power output (RMS):</b>	6 watts
<b>Frequency:</b>	40Hz-300Hz
<b>Impedance:</b>	4Ω
<b>Sensitivity:</b>	400mV
<b>Signal to noise ratio:</b>	65dB

#### Connectivity:

<b>Connection type:</b>	3.5mm
<b>Audio output:</b>	yes

#### Product dimensions:

<b>Speakers:</b>	8.8x13.5x6.8cm
<b>Subwoofer:</b>	15x22.6x20cm
<b>Cable length:</b>	1.2m
<b>Warranty:</b>	One year